



THIS IS CONFIDENTIAL INFORMATION.  
THIS DRAWING AND DESIGN IS THE PROPERTY OF LIQUIP INTERNATIONAL PTY LIMITED.  
IT MUST NOT BE COPIED OR REPRODUCED IN ANY WAY WHATSOEVER AND/OR PASSED ON  
TO ANY THIRD PARTY WITHOUT WRITTEN AUTHORITY.

LIQUIP INTERNATIONAL PTY LIMITED - ENGINEERING DEPARTMENT - 13 HUME RD SMITHFIELD SYDNEY NSW AUSTRALIA 2164  
PH: +61 2 9725 9000 FAX: +61 2 9609 4739 EMAIL: engineering@liquip-nsw.com.au

## LIQUIP DCC100 POWER CONDITIONER

### DATA SHEET & INSTRUCTION LEAFLET

Part No: 59084

<b>TITLE:</b>	Electrical power conditioner																
<b>PURPOSE:</b>	To protect connected equipment from surges and voltage spikes generated by vehicle operation. To supply 12V DC out with low noise and wide range of input voltage from 9V to 36V DC.																
<b>MATERIALS OF CONSTRUCTION:</b>	Heatshrink, Plastic, metal.																
<b>MOUNTING:</b>	<p>The DCC100 is not designed to be exposed to dirt or moisture. It must be either mounted in the cab area, typically in the fuse box, or inside a junction box of IP rating 66 minimum (Liquip JBL100 or similar)</p> <ul style="list-style-type: none"><li>▪ Ensure cable glands are rated for a minimum IP66.</li><li>▪ Wire as per wiring diagram attached.</li><li>▪ Ensure IP66 rated blanking plugs are used in any unused holes in junction box.</li></ul>																
<b>WEIGHT:</b>	0.1 kg (without junction box)																
<b>TECHNICAL DATA:</b>	<table><tr><td><b>INPUT VOLTAGE:</b></td><td>9V-36V DC</td></tr><tr><td><b>OUTPUT VOLTAGE:</b></td><td>12V DC</td></tr><tr><td><b>MAXIMUM LOAD:</b></td><td>Total 1.67A Continuous</td></tr><tr><td><b>VOLTAGE SPIKE PROTECTION:</b></td><td>Protect up to 50V/100ms spike</td></tr><tr><td><b>OUTPUT VOLTAGE NOISE:</b></td><td>Less than 0.1V</td></tr><tr><td><b>RECOMMENDED FUSE RATING:</b></td><td>3.15A slow blow</td></tr><tr><td><b>CABLE SIZE:</b></td><td>0.2– 2.5mm<sup>2</sup>, strip length 6mm</td></tr><tr><td><b>INGRESS PROTECTION:</b></td><td>IP20</td></tr></table>	<b>INPUT VOLTAGE:</b>	9V-36V DC	<b>OUTPUT VOLTAGE:</b>	12V DC	<b>MAXIMUM LOAD:</b>	Total 1.67A Continuous	<b>VOLTAGE SPIKE PROTECTION:</b>	Protect up to 50V/100ms spike	<b>OUTPUT VOLTAGE NOISE:</b>	Less than 0.1V	<b>RECOMMENDED FUSE RATING:</b>	3.15A slow blow	<b>CABLE SIZE:</b>	0.2– 2.5mm <sup>2</sup> , strip length 6mm	<b>INGRESS PROTECTION:</b>	IP20
<b>INPUT VOLTAGE:</b>	9V-36V DC																
<b>OUTPUT VOLTAGE:</b>	12V DC																
<b>MAXIMUM LOAD:</b>	Total 1.67A Continuous																
<b>VOLTAGE SPIKE PROTECTION:</b>	Protect up to 50V/100ms spike																
<b>OUTPUT VOLTAGE NOISE:</b>	Less than 0.1V																
<b>RECOMMENDED FUSE RATING:</b>	3.15A slow blow																
<b>CABLE SIZE:</b>	0.2– 2.5mm <sup>2</sup> , strip length 6mm																
<b>INGRESS PROTECTION:</b>	IP20																
<b>DIMENSIONS:</b>	55W x 65L x 25H (mm)																
<b>ASSOCIATED EQUIPMENT:</b>	DIP200, DIP240, EMH5xx, EMH6xx, MPP102, PPM300 Series, COPS series. JBL100 Junction box IP66 with 3 x M20 holes																

*Wiring diagram shown on the drawing overleaf.*




THIS IS CONFIDENTIAL INFORMATION.  
 THIS DRAWING AND DESIGN IS THE PROPERTY OF LIQUIP INTERNATIONAL PTY LIMITED.  
 IT MUST NOT BE COPIED OR REPRODUCED IN ANY WAY WHATSOEVER AND/OR PASSED ON  
 TO ANY THIRD PARTY WITHOUT WRITTEN AUTHORITY.

LIQUIP INTERNATIONAL PTY LIMITED - ENGINEERING DEPARTMENT - 13 HUME RD SMITHFIELD SYDNEY NSW AUSTRALIA 2164  
 PH: +61 2 9725 9000 FAX: +61 2 9609 4739 EMAIL: engineering@liquip-nsw.com.au

# LIQUIP

## DCC100 WIRING DIAGRAM



**X350409**

Issue: A

NOTE: THIS IS A GENERAL WIRING DIAGRAM ONLY.  
 ANY WIRING INSTRUCTIONS FOR SPECIFIC EQUIPMENT SUPERSEDE THIS DIAGRAM.

METERS - VALVES - VENTS - MANHOLES - PUMPS - HOSEREELS - OVERFILL PROTECTION - LOADING ARMS - ELECTRONIC DIPSTICKS



LIQUIP INTERNATIONAL PTY LTD  
 13 Hume Road  
 Smithfield, 2164  
 Sydney NSW Australia  
 Phone: +612 9725 9000  
 Fax: +612 9725 1252

DISTRIBUTORS  
 See inside front cover  
 for Liquip branches  
 and Distributors  
 www.liquip.com